MOUNTS / MICROPHONE CAPSULES / CABLE AND CONNECTOR DISPLAY UNITS

PROX-60

NETO: 0,00

AMPLIFICADOR DE MEGAFONÍA MONOZONA



DESCRIPTION

PA amplifier with USB/FM player

BENEFITS
The perfect solution that integrates an amplifier, mixer, music player, microphone and aux inputs into just one unit. For PA installations with 100 V or low impedance speakers where intuitive operation and a tight budget are top priorities.
Euroblock connectors, safe and easy to connect.
Excellent sound quality.
A design that is both modern and discreet.
Compact size, for desktop use.

APPLICATIONS
PA and piped music systems with 100 V or low impedance line speakers. Retail shops, educational centres, monuments, exhibitions, bars, restaurants, etc.

TECHNICAL DATA
60 W RMS
Microphone input with mix, gain and priority level control.

Expand product information on:
https://fonestar.com/es/PROX-60

Tone controls.
100 V and 4 Ohm outputs.
100 V line input with priority and contact closure mute for integration in installations with emergency alerts.

TECHNICAL CHARACTERISTICS

FEATURES	Public Address Amplifier USB/FM player. Microphone inputs with mix, gain and priority level control. Tone controls. 100 V and 4 Ohm outputs.
POWER	60 W RMS
RESPONSE	20-20,000 Hz ± 3 dB
DISTORTION	Harmonic: <1% at 1 kHz
INPUTS	1 balanced / unbalanced mic, euroblock / 6.3 mm jack, 600 Ohm 6 mV RMS 1 balanced mic, euroblock, 600 Ohm 6 mV RMS 2 aux, euroblock / 2 x RCA, 47,000 Ohm 300 mV RMS 1 x 100 V line , euroblock
FUNCTIONS	Input priority. Emergency Input 100V with maximum priority, attenuates all other inputs. Mute by contact closure, attenuates all inputs except the 100V Emergency input. Microphone 1 and 2 with priority over Aux and Playback inputs, by signal level, selectable. Power on, protection, signal peak and output signal indicator lights. Fanless induction cooling
CONTROLS	Microphone volume Selected input volume Input selector USB/FM player controls Tone: bass and treble Microphone gain and priority
PLAYER	USB player with ambient music playback mode. When turned on, it automatically starts playback in successive order FM digital tuner with presets and automatic search Memory of last selected mode (USB or FM), last played song or last tuned station and last selected playback mode

Expand product information on:
https://fonestar.com/es/PROX-60

IMPEDANCE	4 Ohm and 100 V line, euroblock
POWER SUPPLY	230/115 V AC, 200 W
DIMENSIONS	286 x 84 x 225 mm depth
WEIGHT	4.4 kg
ACCESSORIES	FM antenna

Expand product information on:
https://fonestar.com/es/PROX-60