HIGH POWER / MIXERS / STUDIO

MIX-6LIVE

STUDIO MIXER.



- 4 mono channels and 1 stereo channel with independent volume controls
- Bluetooth® receiver and USB recorder/player
- 16 digital effects processor
- USB audio for connection to PC as audio card
- Live streaming function

ESPECIALLY RECOMMENDED IN:

Hospitality

Sports facilities

Education

Hotels

+ Info:
https://fonestar.com/MIX-6LIVE

DESCRIPTION

6-channel stereo mixer with live streaming function, PC audio card and Bluetooth®/USB recorder/player .

Live Streaming feature, you can connect your smartphone or tablet and stream your live performance to your favourite platform, with no need for anything else.
Connect the mixer to your PC as a Plug and Play audio card on Windows and Mac. You can play audio content from your PC and record audio on your PC simultaneously.
Bluetooth/USB recorder and player, plays music or records the performance without PC.

It features a 24-bit digital effects processor (16 effects) with effects selection and level control, which will give an extra touch to your performances.
In addition, 48 V phantom power is available on channels 1 and 2 for the use of condenser microphones.

It has a small and portable size, perfect for street performers, home music studios, small events or parties, etc. In addition, it only requires a 5V DC, 2.1 A power supply, which can be provided by the adapter, by the USB port of a PC or laptop or through a power bank, which greatly increases the versatility and possibilities of use of this complete mixer

TECHNICAL CHARACTERISTICS

FEATURES	4-channel mono and 1-channel stereo mixer. Live streaming function, connect your smartphone for live streaming. USB audio input/output for PC connection as Plug and Play audio card on Windows and Mac, allows simultaneous audio playback from PC and recording. 4.2 Bluetooth Receiver USB recorder/player. 16 digital effects processor.
USB PLAYER	Plays or records MP3 files USB-C port for PC connection as Plug and Play audio card on Windows and Mac Stereo line-level auxiliary input
INPUTS	4 balanced micro/lines, combo (XLR, 600 Ohm 15 mV RMS and 6.3 mm jack, 47.000 Ohm 200 mV RMS) 1 balanced stereo line channel, 2 x 6.3 mm jack, 47,000 Ohm 250 mV RMS 1 stereo auxiliary, 3.5 mm jack, 47,000 Ohm 1 V RMS 1 stereo auxiliary (live streaming), 3.5 mm TRRS jack, 47.000 Ohm 250 mV RMS 1 microphone, 3.5 mm jack TS, 600 Ohm 15 mV RMS 1 USB/PC, stereo
CONTROLS	6 controls per channel: gain, 3-band EQ, pan, volume, and clip light indicator Effects and level selection Headphone volume Independent volume control for main and aux/monitor output
FUNCTIONS	3-band equaliser per channel Overload light indicator and master output level light indicator Live streaming USB/PC

+ Info:
https://fonestar.com/MIX-6LIVE

OUTPUTS	1 balanced/unbalanced stereo main, 2 x 6.3 mm jack/2 x RCA, 2.5 V RMS 1 balanced aux/monitor, 6.3 mm jack, 2 V RMS 1 stereo auxiliary (live streaming), 3.5 mm TRRS jack, 0.5 V RMS 1 stereo headphone, 3.5 mm jack 1 USB/PC, stereo
PHANTOM	48 V on channels 1 and 2, selectable
RESPONSE	20-20,000 Hz
DISTORTION	Harmonic: 0.04 %
S/N RATIO	> 65 dB
POWER SUPPLY	5 V DC, 2.1 A with included adapter
DIMENSIONS	210 x 70 x 237mm depth
WEIGHT	1.1 kg
ACCESSORIES	3.5 mm TRRS male-to-male audio jack cable USB-A to USB-C power cable USB power adapter

+ Info:
https://fonestar.com/MIX-6LIVE