PRODUCT TECHNICAL DATASHEET

# B71/BC/INT



| CODE | DESCRIPTION | PCS/PALLET |
|---|---|---|
| **B71/BC/INT** | Kit for emergency batteries charger for Brushless digital controller 24V DC with plug-in cord, with 2 recovery batteries 12V DC, 1,2 Ah. Box case included. | |

| PRODUCT TECHNICAL SPECIFICATIONS | |
|---|---|
| Power line supply | 16V AC … 24V AC |
| Operating temperature | -20°C +55°C |
| Maximum input power | 15W |
| Lead-acid batteries | 2 x 12V DC 1200mAh, connected in series (external B71/B |
| Nominal charge voltage | 27.6 V DC |
| Minimum self-protection voltage of battery | 19.5 V DC |
| “br” open jumper charge current | 250 mA (for 1200mah batteries) |
| “br” close jumper charge current | 400 mA (optional, for fast charge of 4500mAh batteries) - B71/BC/EXT |
| Maximum dimension product in mm (L x W x H) | 243 x 49 x 89 |
| Product weight packed (Kg) | 1.5 |

# PRODUCT ACCESSORIES

Batteries, Chargers and Inverter