HIGH POWER / MIXERS / STUDIO

MIX-4LIVE

STUDIO MIXER







BLUETOOTH USB REC LIVE STREAM PC

- 2 mono channels and 1 stereo channel with independent volume controls
- Bluetooth® receiver and USB recorder/player
- USB audio for connection to PC as audio card
- Live streaming function

+ Info:
https://fonestar.com/MIX-4LIVE

ESPECIALLY RECOMMENDED IN:



Hospitality



Sports facilities



Education



Hotels

DESCRIPTION

Studio mixer. 2 mono channels. 1 stereo channel. 2 microphones. USB player/recorder and Bluetooth® receiver. Live streaming function. USB audio input/output for PC connection as an audio card. 2 digital effects (delay and repeat).

TECHNICAL CHARACTERISTICS

FEATURES	2-channel mono and 1-channel stereo mixer. Live streaming function, connect your smartphone for live streaming. USB audio input/output for PC connection as Plug and Play audio card on Windows and Mac, allows simultaneous audio playback from PC and recording. 4.2 Bluetooth Receiver USB recorder/player. 2 digital effects (delay and repeat).
USB PLAYER	Plays or records MP3 files from USB USB-C port for PC connection as Plug and Play audio card on Windows and Mac
INPUTS	2 balanced microphones/lines, combo (XLR, 600 Ohm 5 mV RMS and 6.3 mm jack, 47,000 Ohm 30 mV RMS) 1 balanced/unbalanced stereo line channel, 2 x 6.3 mm jack/2 x RCA, 47,000 Ohm 300 mV RMS 1 stereo auxiliary for live streaming, 3.5 mm TRRS jack, 47,000 Ohm 300 mV RMS 1 mic, 3.5 mm mono jack, 600 Ohm 5 mV RMS 1 USB/PC, stereo
CONTROLS	4 controls per channel: gain, 2-band EQ, volume, and clip indicator light Effects level control Headphone volume Independent main output volume control
FUNCTIONS	2-band equaliser per channel Overload indicator and master output level indicator light Live streaming USB/PC
OUTPUTS	1 stereo main balanced/unbalanced, 2 x 6.3 mm jack/2 x RCA, 5 V RMS 1 stereo auxiliary for live streaming, 3.5 mm TRRS jack, 500 mV RMS 1 stereo headphone, 3.5 mm TRRS jack, 500 mV RMS 1 USB/PC, stereo



+ Info:
https://fonestar.com/MIX-4LIVE

PHANTOM	48 V on channel 1, selectable 5 V at 3.5 mm jack plug on channel 1
RESPONSE	20-20,000 Hz
DISTORTION	Harmonic: 0.05 %
S/N RATIO	> 68 dB
POWER SUPPLY	5 V DC, 2.1 A with adapter included
DIMENSIONS	175 x 55 x 190 mm depth
WEIGHT	0.6 kg
ACCESSORIES	3.5 mm TRRS male-male audio cable USB-A to USB-C power cable USB power adapter



+ Info:
https://fonestar.com/MIX-4LIVE