VELA-BUP

NETO: 0,00

AMPLIFICADOR DE RESERVA PARA SISTEMA DE MEGAFONíA Y ALARMA POR VOZ EN 54 VELA



DESCRIPTION

EN54 Backup amplifier.

FEATURES
VELA is a voice evacuation system certified in accordance with the EN54 fire protection standard. A perfect solution for PA evacuation systems that include zones. Dante compatible, and ethernet connection for PC software configuration and control. Among the principal functions, worth pointing out is emergency and evacuation announcements with zone control. System status check and loudspeaker line monitoring. Input and output DSP functions. Playback of pre-recorded messages, microphone and line inputs, and automatic switchover from the backup amplifier.

The backup amplifier VELA-BUP guarantees a power supply in case the main amplifiers VELA-AMP or VELA-EXT fail.
In addition, it can be configured for an alert function + background music.
One VELA-BUP backup amplifier is required per VELA-AMP central amplifier or VELA-EXT extension of the voice alarm system.

APPLICATIONS
Designed for PA and voice evacuation installations in accordance with the EN54 fire protection standard. For medium- and large-sized installations such as shopping centres, stadiums, convention centres, hospitals, residences, etc.

Technical data:
360 W RMS

TECHNICAL CHARACTERISTICS

Expand product information on:
https://fonestar.com/es/VELA-BUP

CHARACTERISTICS	EN 54 Backup amplifier for PA system and voice alarm. EN 54-16 certified.
POWER	360 W RMS
RESPONSE	100-15,000 Hz
INPUTS	1 PA IN for mod. VELA-AMP or VELA-EXT, RJ-45
POWER SUPPLY	230 V AC, 1100 W and 24 V DC, 22 A
DIMENSIONS	483 x 89 x 335 mm depth. 2 U 19" rack
WEIGHT	14.4 kg

Expand product information on:
https://fonestar.com/es/VELA-BUP