MICROPHONE / WIRELESS MICROPHONES / ACCESSORIES

FCM-970-MC3

FLESH-COLOURED HEAD-WORN CONDENSER MICROPHONE





1,2 M CABLE

PHANTOM

1-10 V DC

- High sensitivity, omnidirectional
- Mini XLR 3-pin connector for mod. SONAIR-PRO
- Elegant design
- Flesh colour
- Adjustable

ESPECIALLY RECOMMENDED IN:

All sectors

+ Info:
https://fonestar.com/FCM-970-MC3

DESCRIPTION

Flesh-coloured head-worn microphone.A lightweight, flesh-coloured microphone that goes unnoticed by both the user and onlookers.Special design to be placed on the head and position the capsule close to the mouth. It picks up sound in all directions so that no detail is lost, even when the speaker moves.It offers great sound pickup.It can be used on wireless microphones or electret condenser microphone inputs, such as portable amplifiers.

TECHNICAL CHARACTERISTICS

FEATURES	Miniature omnidirectional electret condenser capsule. For wireless microphones or electret condenser microphone inputs. Flesh colour. Adjustable.
RESPONSE	20-20,000 Hz
SENSITIVITY	-42 dB ±2 dB (V/Pa)
IMPEDANCE	1,000 Ohm
POWER SUPPLY	1 to 10 V DC
CABLE	1.2 m
MATERIAL	Steel
CONNECTOR	3-pin female Mini XLR connector Pin 1: ground (GND). Pin 3: signal
COMPATIBILITY	FCM-970-TS, Jack 3'5 mm mono for mods. MSHT-45P/MSH-135 FCM-970-TSM, 3'5mm mono jack with male thread for mods. SONAIR FCM-970-MC3, mini XLR 3-pin for mods. SONAIR-PRO, AKG and Gemini FCM-970-MC4, mini XLR 4-pin for mod. MSH-236 FCM-970-MC4S, mini XLR 4-pin for mods. Shure and JTS
ACCESSORIES	Wind-shield foam

+ Info:
https://fonestar.com/FCM-970-MC3