
PH206

Operator Phone

Multi Function Business Phone



Product Parameter

Basic Parameter	
Type:	Business Phone
Model:	PH206
Place mode:	Lay flat in three level, Wall mounted
Size:	18.3 x 22.5 x 10 cm
Net weight:	0.8kg
Warranty:	3 months



Product Function

1. Functional keys : work with Excelltel PABX . Like forwarding , pick up , DND
2. DTMF/FSK Caller ID
3. 38 incoming call records
4. 16 outgoing call records
5. Real time display of date and time
6. 16 volume adjustable rings
7. 16 music rings for selection
8. 11 pre-store speed dial number
9. 8 digital local area code filter
10. build in hold on music
11. 14 digital , 5 brightness level LCD display

Backlight when hang on



Product Appearance



Functional Keys

It will work when connect with Excelltel PABX

LEAVE FORWARD Means input * #91 automatically. Then user input the forwarding extension number	DND(do not diturb) Means input * #31 automatically. Then the extension will in DND mode . Input #31# means cancel it.
CANCEL FORWARD Means input * #90 automatically. Cancel leave / busy forward function.	BUSY FORWARD Means input * #92 automatically. Then user input the forwarding extension number .
PICK UP Means input * #1 automatically. Then it will pick up the phone from another extension	

Normal Keys

SET SET	DEL It can delect records of incoming calls or outgoing calls
INCOMING Input this key , it can check the records of incoming calls	OUTGOING Input this key , it can check the records of outgoing calls
PAUSE Input this key , It will pause the conversation . Input again and continue .	CALL BACK Input this key , it can call back the last incoming number
TRANSFER Input this key mean put the hook then dial the extension number you want to transfer	REDIAL Input this key , it can redail the last outgoing number
HOLD Input this key to hold the current conversation	

Memory Button

Save the frequently used number on the button for speek dialing .



M1-M11: Total can save 11 numbers . After saving, you can call that numbers automatically .

For exmapl : save the number 00 86757 86228930 to M1

1. No need pick up and input the number 00867578628930 directly. Then the display screen will show this number .

2. Long Pressing the button M1 for 3 seconds until disperance on the screen .

3. If you want to dial the number 00867578628960 , you can input the button M1 directly .

Product Real View



White

Black

Packing List